

# MKC for VVX



Key Combination for Phone Reboot  
Models Supported : VVX 300,310,400,410,500,600



Key Combination for Phone information  
Models Supported: VVX 300,310,400,410,500,600

Only  
Soft  
ware  
5.3.0  
or  
later



Key Combination to Set Base Profile  
Models Supported: VVX 300,310,400,410,500,600



Key Combination for Reset To factory  
Models Supported: VVX 300,310,400,410,500,600



Key Combination for Upload Log File  
Models Supported: VVX 300,310,400,410,500,600



Key Combinations to Restart the Phone  
Models Supported : 300,310,400,410,500,600

# Factory Reset Trio and Visual+

## Resetting the Trio or the Visual+

- Power Cycle Trio
- Wait for Polycom Logo
- Hold all 4 corners of the touch screen until mute lights start flashing different colors, then let go
- Let it reboot on its own



- Power Cycle Visual+
- Wait for the initial light to come on then off again on the pair button
- Press and hold the pair button down immediately and let go when the pair button cycles
- The Visual+ will automatically reboot and start when complete

